

6x15w Laser Beam RGBW Moving Head Lighting



Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

Statement

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual, any misuse cause of the damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual.

Attention Item

1. For guarantee the life of product,please do not put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.
4. Power supply should not be changed over +&-10% while the light is using,it will be decreased the life of lamp if the power is too high,but it will be influenced the luminosity if the power is too low.
5. After power off,if it is need used again,please cool down over 20 minuter.
- 6.Please look round the manual for ensure the product can be used normally.

Display Control Instruction

Welcome to use our light.The light uses energy-saving LED,long Product life,shockproof,dustproof, DMX receiver and self-running feature, which can produce a variety of vivid lighting effects,easy to operate, suitable for all types of entertainment decoration,architectural lighting industry.

Access control panel functions using the four buttons located directly underneath the LED display on the included wired remote.

BUTTON	FUNCTION
<MENU>	Used to scroll through the current operating mode, as well as back out of the current menu option
<DOWN>	Used to select decreasing advancement in the value
<UP>	Used to select increasing advancement in the value
<ENTER>	Used to select a value and store it to memory



The Control Panel shows the current state of the unit. It is used to select the operating mode, as well as the sub-features. For a detailed layout of the control panel functions, please see the "menu map" section on the following page.

Instructions:Press the function key A cycled out the eight different function effects,digital tube first two digits on behalf of which the current function(see menu).The last two digits represent the functions in which the address code or speed parameters.Press the B or C key to modify the parameter values.Press the D key to confirm.

Product Introduction

- * **Power Supply:**AC90--275V,50--60HZ
- * **Power consumption:**90W
- * **Drive Current:**2000mA
- * **Color Temperature:** 6500k
- * **Beam Angle:**120 Degrees
- * **Control Modes:**DMX512,Auto Run,Sound Action,Strobe, Stand Alone and Master/Slave,With Rich Advanced Built-in Program
- * **Strobe:**Flash rate 0--20HZ
- * **DMX-Control-channels:**13DMX Channels
- * **Tilt :** 270° (16bit)
- * **Pan :** 540°(16bit)
- * **Dimmer:**0-100% mechanic dimmer
- * **Long Lifespan LEDs**(more than 60,000 hours)
- * **Waterproof level:**IP20 Indoor
- * **Ambient temperature:** -20°C ~ 40°C
- * **Cooling System:**Box Heat Conduction
- * **Shell Material:**Flame-retardant Engineering Plastic Shell
- * **Product Color:**Black
- * **Long Lifespan LEDs**(more than 60,000 hours)
- * **Product Size:**30x25.5x20cm
- * **Product Weight:**3.2kg
- * **Package Size:** 33X28x23cm
- * **Package Weight:** 4 kg
- * **Certificate:** CE & ROHS & UL & FCC & EAC & SAA
- * **Warranty:** Within 1 year.[we are free to repair, provide any accessories; or send new products.]
- * **Plug:** To send you to meet the requirements of the plug, EU,US,AU,UK Plug and so on.
- * **Use Of Premises:** Outdoor ,Party,DJ,Bar,Clubs,Hotels,Restaurant, Church,Concert,Stages.

Display Control Instruction

Menu	Function Value	Function
Addr	R001-R512	512 Address Setting
R100	1-9	Auto Mode (Function Selection)
S100	1-9	Sound Control Mode (Function selection)

1	Pan Motor	0-255	0~255 0-540° Spin
2	Tilt Motor	0-255	0~255 0-180° Spin
3	Pan&Tilt Motor Speed	0-255	0~255 From Fast to Slow
4	Z axis motor	0-255	0~127 0-360° Rotation, 128-191 Forward Rotation from Slow to Fast, 192-255 Reverse Rotation from Fast to Slow
5	Total Dimmer	0-255	Linear Dimming from Dark to Bright
6	Strobe	0-9	No Features
		10-255	From Slow to Fast
7	Red	0-255	Red Dimmer From Dark to Bright
8	Green	0-255	Green Dimmer From Dark to Bright
9	Blue	0-255	Blue Dimmer From Dark to Bright
10	White	0-255	White Dimmer From Dark to Bright
11	Green Laser	0-255	Green LaserDimmer From Dark to Bright

12	Macro function control	0-50	Channel 1 to Channel 11 Vaild
		51-150	Random Self Running
		150-255	Sound Control Self Running
13	Reset	0-250	NONE
		251-255	3 Second reset
<p>Menu: A001-A512 Address Setting A 1-A 9 Self Running Mode S1 1-S1 9 Sound Contolr Mode Digitally set the voice control density</p>			

DMX Channel Summary-16 Channels Mode