

DMX Channel Summary- (d) 38 Channels Mode

Channel	Value	Function
1	0-255	Horizontal operation
2	0-255	Horizontal speed
3	0-10	no effect
	11-20	Built-in effect 1
	21-31	Built-in effect 2
	32-42	Built-in effect 3
	43-53	Built-in effect 4
	54-64	Built-in effect 5
	65-75	Built-in effect 6
	76-86	Built-in effect 7
	87-97	Built-in effect 8
	98-108	Built-in effect 9
	109-119	Built-in effect 10
	120-130	Built-in effect 11
	131-141	Built-in effect 12
	142-152	Built-in effect 13
	153-163	Built-in effect 14
	164-174	Built-in effect 15
	175-185	Built-in effect 16
	186-196	Built-in effect 17
	197-207	Built-in effect 18
	208-218	Built-in effect 19
	219-229	Built-in effect 20
	230-240	Built-in effect 21
241-250	Built-in effect 22	
251-255	Voice control effect	

4	0-255	Built-in effect speed
5	0-255	Total dimming
6	0-255	Strobe
7	0-255	BAR1 R dimming
8	0-255	BAR1 G dimming
9	0-255	BAR1 B dimming
10	0-255	BAR1 W dimming
11	0-255	BAR2 R dimming
12	0-255	BAR2 G dimming
13	0-255	BAR2 B dimming
14	0-255	BAR2 W dimming
• • •	• • •	• • •
35	0-255	BAR8 R dimming
36	0-255	BAR8 G dimming
37	0-255	BAR8 B dimming
38	0-255	BAR8 W dimming

DMX Channel Summary-(g)9 Channels Mode

Channel	Value	Function
CH1	0-255	Horizontal operation
CH2	0-255	Speed adjustment
CH3	0-255	Built-in effects
CH4	0-255	Built-in effect speed adjustment
CH5	0-255	Total dimming
CH6	0-255	Red dimming
CH7	0-255	Green dimming
CH8	0-255	Blue dimming
CH9	0-255	White dimming